

# Configuration de base d'un élément actif Cisco

Voici une configuration de base utilisable en copié/collé pour réaliser vos pré-configuration.

Elle permet de mettre le nom de la machine, le mot de passe pour le mode configuration, le mot de passe pour le mode console et le mot de passe pour les sessions vty (ici, 2 autorisé seulement).

On demande aussi à ne pas être dérangé lors de l'utilisation de la console par les messages systèmes.

Aussi, la bannière indispensable pour indiquer les risques encouru par un utilisateur non autorisé.

```
conf t
```

```
hostname X
```

```
enable secret XYXYXYXYXY
```

```
banner motd % =====Toute personne non autorise se verra poursuivi en fonction des lois en  
vigueur ===== %
```

```
service password-encryption
```

```
no ip domain-lookup
```

```
line console 0
```

```
password XXXXYXXXXX
```

```
login
```

```
logging synchronous
```

```
line vty 0 2
```

```
password YYYYYXXXXYY
```

```
login
```

```
logging synchronous
```

```
exit
```

---

Revision #1

Created 31 October 2019 13:33:27 by Cécile

Updated 31 October 2019 13:34:30 by Cécile